




# IBM STANDARD COMPUTER COMM PORT TO BART A AND B "SER" PORT

BART RS-232 SERIALS A AND B TELCO RECEPTACLES TO COMPUTER COM DB9M  
(REQUIRES A DB9F TO A TELCO PLUG ON CABLE)

COMPUTER



BART TELCO RECEPTACLE  
VIEW: OUTSIDE BACK  
OF BART



COMPUTER DB9M		CABLE WIRE COLOR	BART TELCO RECEPTACLE SERIAL A AND B	
PIN	SIGNAL		PIN	SIGNAL
6. & 8.	*	BLUE	1.	NC
5.	GND	YELLOW	2.	GND
3.	TXD	GREEN	3.	RXD
2.	RXD	RED	4.	TXD
5.	GND	BLACK	5.	GND
4.	DTR	WHITE	6.	+5VDC

(STANDARD 6 CONDUCTOR TELCO CABLE USED)

(\* NOT REQUIRED)

CABLE APPLICATION:  
THIS CABLE IS USED TO CONNECT A STANDARD IBM RS-232 DB9M CONNECTOR TO A BART RS-232 TELCO CONNECTOR

TRIAD PRODUCTIONS, INC.		
Title BART SER A AND B TO COMPUTER COM DB9M		
Size A	Document Number BARTTEL.OCD	REV A
Date:	November 3, 1995	Sheet 1 of 1